FAIRFILD

DATASHEET - RMS

Wirewound naked resistor

RMS

Description

Stainless steel terminals for screws M6, Very robust design for high energy pulses and heavy overload, Suitable for group assemblies

Mechanical characteristics

IP00, Wire wound on ceramic support mounted on a metallic bar

Applications

Dynamic braking, Neutral Grounding, Starting Motor, Charge/discharge capacitors, Load Bank

Market

ε

fo@fairfild.co

2

. c o m -

rfild

fai

M M

≥

Railways, Industrial automation, Energy

Special version

Fixing slots different, Adjustable, Not inductive, Mica bar



0.5 ÷ 3.5 KW

4

00

4

0

ດ

3

+

Ð

hon

ELECTRICAL CHARACTERISTICS

refers to room temperature 25°C Min not inductive Max not inductive ID Rated Power Min Resistance Max Resistance Resistance Resistance Unit kW Ω Ω Ω Ω RMS 5 500 ÷ 1500 1 47 4 12 RMS 6 650 ÷ 2000 1.2 56 4.8 14 RMS 7 800 ÷ 2300 1.5 68 6 17 RMS 8 950 ÷ 2800 1.8 82 7.2 21 RMS 9 1000 ÷ 3100 2 100 8 25 **RMS 10** 1200 ÷ 3500 2.2 110 8.8 27 Limit Voltage 2000 V (3000 V for mica bar version) Insulation resistance 1000 VDC≥1000 MΩ

Temp. Coefficient Resistance: low ohmic value are made with active material CuNi44 that has a TCR of 40 ppm/°C, whereas high ohmic value refers to wire material FeCrAI that has a TCR of 70 ppm/°C. Resistors can be made also with NiCr alloys with TCR between 70 and 240 ppm/°C.

Rated power depends on total surface area according to Newton's law

$$\frac{dQ}{dt} = h \cdot A \cdot (T_{env} - T)$$

Where

Q is the thermal energy in joules

h is the heat transfer coefficient ($W/m^2 K$)

A is the surface area of the wire (m^2)

 T_{env} is the temperature of the environment T is the temperature of the wire

In the case of model RMS, the total surface area depends on the ohmic value according to Ohm's law

$$R = \rho \cdot \frac{l}{S}$$

Where R is the resistance

 $\boldsymbol{\rho}$ is the resistivity of the used alloy

I is the length of the conductor (wire) S is the cross section of the conductor (wire)

The number of the turns in the RMS model is fixed and depends on the diameter of the wire.

As a result, the lower is the ohmic value, the higher is the surface area then the power. At the contrary the higher is the ohmic value, the lower is the surface area and then the power.

In the above table min and max rated power refer to wire temperature 600 °C and resistor placed in free air, in the graph of rated power is shown the power that corresponds to a temperature of wire of 600 °C for ohmic values from the minimum to the maximum.

The same reason is for the energy absorption. Lower ohmic values have higher mass of active material because

 $m=S\cdot l\cdot\rho$



Wirewound naked resistor

Where

 $\begin{array}{l} m \text{ is the mass of active material} \\ S \text{ is the cross section of the conductor (wire)} \\ I \text{ is the length of the conductor (wire)} \\ \rho \text{ is the density of active material} \\ \end{array}$

FAIRFILD

In the graph of pulse load is shown the energy in kJ that corresponds to a ΔT of the wire of 900 °C according to the law

 $\Delta E = m \cdot cp \cdot \Delta T$

Where ΔE is the amount of energy that enter in the resistor m is the mass of the wire cp is the specific heat of the wire ΔT is the over-temperature of the wire

This equation is valid only when the pulse is very short (< 0.5 s) and it is called adiabatic, it means that all the energy is dissipated by the wire itself. When the pulse duration is longer, the wire can exchange the energy with the surrounding ambient, then the energy that can be dissipated is higher.

For pulse duration less than 60 s, the mass of the wire is determinant to calculate the overload conditions.

Please contact Fairfild technical office for more details.

MECHANICAL DATA

Unit [mm]	A [mm]	B [mm]	C [mm]	Weight [g])
RMS 5	340	380	20	1050] <
RMS 6	400	440	20	1200	
RMS 7	460	500	20	1350	
RMS 8	520	560	20	1500];
RMS 9	580	620	20	1600	
RMS 10	650	700	27	1700	

Unless otherwise specified, applicable standard of general tolerances for linear and angular dimensions is ISO 2768-1 class c.

Different slots positions are available: Axial - Axial, or Transversal - Transversal. Picture at page 1 refers to RMS Axial Axial.

Weight indicated in the table is an approximate data, the exact data depends on wire mass and on the material of bar. Mica bar allows to save weight.

DRAWING



۵.

5 7

H



www.fairfild.com- info@fairfild.com

~

S

4071

00

4 2

0 **6**

3

+

× a

Ц., 1 T

~ Н

0

4

00 4

2

0

0 3

÷

Phone

Wirewound naked resistor

FAIRFILD

4.000 RMS 5 RMS 6 3.500 RMS 7 RMS 8 3.000 RMS 9 **RMS 10** 2.500 Power (W) 2.000 1.500 1.000 500 0 5 25 1 125 Ohmic value (Ω)

POWER VS. OHMIC VALUE (WIRE TEMP. 600°C)

PULSE LOAD GRAPH (ΔT WIRE 900 °C)



www.fairfild.com- info@fairfild.com





DATASHEET – RMS

Wirewound naked resistor

Marking

The resistor is marked on the collar with indelible ink high temperature FAIRFILD – RMS 5 15R 5% WW/YY (week / year)

Installation

In case of group mounting keep a distance of at least 30 mm between consecutive resistors.

Packing

The resistor is packed in a way to preserve incidental damages due to transport. The resistor is made by ceramic parts, accidental fall can damage it, handle with care.

Disclaimer

Every effort has been made to ensure that the information in this datasheet is accurate. Fairfild is not responsible for printing or clerical errors. All properties and characteristics mentioned in this datasheet are only for informational purposes. The information in this datasheet is offered solely for your consideration and should not be taken as a warranty or representation for which we assume legal responsibility. The customer bears all responsibility for use and application of Fairfild products. There is no responsibility of the manufacturer for any damage to persons and properties in case of improper use. Fairfild reserves the right to change specifications without prior notice.

Copyright

C

www.fairfild.com-

This datasheet is subject to copyright. Fairfild reserves all rights of translation in any language, reprinting, re-use of illustrations.

No part of this publication may be reproduced or transmitted in any form or by any means, electronic, mechanical, photocopying, without the written permission of the copyrighted owner Fairfild, Italy. Violations may be subject to legal proceedings involving monetary damages as well as compensation for costs and legal fees under Italian copyright law and regulation within the European Union.

Ordering Information

RMS/Y M RRRR 5% (mica)

- R : adjustable version N : not-inductive version
- MICA (at the end of description) :
- M Model 5, 6, 7, 8, 9, 10

RRRR Resistance value (nominal at 20°C)

Example RMSN 5 15R 5% RMS is the name of the product N means the resistor is made in not inductive version 15R means 15 Ω that is the nominal ohmic value at 20°C 5% is the tolerance on the ohmic value, in this case the value of the resistor is accepted when is within 14.25 Ω ÷ 15.75 Ω

Note: tolerance on ohmic value for adjustable resistors is normally -0+15%; tolerance on ohmic value for standard resistor is normally $\pm 5\%$

Picture at page 1 refers to RMS 6 Axial Axial stainless steel bar.

